

FOX 180S

MMA
MIG

Multiprocess Inverter



Automotive



EN 60974 -1
EN 60974 -10



Line Voltage Compensation
-M+ %



6013 - Rutile



		FOX 180S
	(1 ph)	230V 50/60Hz
Power 60%	KVA	3,5
Uo	V	25/40
Amp. Min - Max	A	5 ÷ 170
Amp. 60974-1	A	25% 170 60% 110 100% 85
Aluminium	Ø mm	0,8 ÷ 1,0
Steel	Ø mm	0,6 ÷ 1,0
Flux core	Ø mm	0,8 ÷ 1,0
Stainless Steel	Ø mm	0,8 ÷ 1,0
Brazing	Ø mm	0,8 ÷ 1,0
MMA - Ø E TYPE: Rutile (6013)	MMA - Ø mm	1,6 ÷ 3,25
Insulation	-	H
Protec. Degree	-	IP22S
	mm (LxWxH)	480X220X385
	mm (LxWxH)	590X260X455
	kg	11,5
kit Code	N°	99820009